HT-446S/SCR

PMR446 / 199 CHANNEL **PROFESSIONAL 2-WAY RADIO PC PROGRAMMABLE**

HT-446S/SCR) PMR446 / 199 CHANNEL **PROFESSIONAL 2-WAY RADIO** PC PROGRAMMABLE

PMR446 handheld transceiver, light and compact, professional construction with die-cast aluminum chassis. LCD display and 4-key user friendly keypad. Transmitter MOSFET circuit design provides high RF output power with minimum current drain for extended battery life. 199 channel (16 channel factory pre-programmed), every function in every channel is programmable by PC (frequency, CTCSS, DCS, Squelch level, ANI, ecc.) with optional programming kit. Set comes complete with rechargeable Li-Ion 1200mAh battery pack and 230VAC desk type rapid charger.

PC PROGRAMMABLE WITH OPTIONAL PROGRAMMING KIT CDLS-HTH



199 channel (16 channel factory pre-programmed)

- TX power 0.5W ERP / 4W-1W (*)
- Dot Matrix Backlighted LCD display with Battery Meter
- MOSFET transmitter circuit design
- 50 CTCSS tones (Encoder/Decoder) / 106 DCS tones (Encoder/Decoder) ٠
- Emergency Alarm function / Monitor function
- SCRAMBLER function (*)
- VOX function with adjustable sensitivity level •
- Channel Naming / ANI (Identification Number) / TOT (Time-Out-Timer) •
- SCAN / Busy Channel Lockout / Power Save
- Dual color RX/TX LED indicator
- PC programmable (with optional programming kit)
- Programmable functions : Channel / Squelch threshold level / LCD Backlight / Keypad tone / SCAN / Keypad Lock / Scrambler (*) / VOX level / Channel Naming / TX 4W-1W RF output power (*) / CTCSS (Encoder/Decoder) and DCS (Encoder/ Decoder) tone / Power Save / TOT (Time-out-Timer) / ANI (Identification Number / Narrow-Wide Bandwidth (*) / Busy Channel Lockout
- External earset-microphone jack
- Rubber flexible fixed antenna
- Operating temperature -20/+60°C
- Dimensions : H 248 x L 58 x P 38 mm / Weight : gr. 230 (with battery pack)

CONTENTS OF THE PACKAGE : Handheld Transceiver with Rubber Fixed Antenna 7.4V 1200mAh Li-Ion Battery Pack 230VAC Electronic Quick Desk Charger Belt Clip, Earset-Mic Jack Cover, User Manual

(*) INTERNATIONAL VERSIONS 400-470 MHz / 4W -1W / Wide Narrow Bandwidth selectable Functions marked (*) are not available in the European CE/R&TTE version

OPTIONAL ACCESSORIES :

- LN-865 High Capacity Li-Ion 7.2V 1800mAh rechargeable battery pack
- KME-315 External Earset-Microphone with tie clip
- External Earset-Microphone with adjustable ear hook KMF-614
 - KME-801 External Earset-Microphone for security and bodyquard
- KME-100A External Earset-Microphone with tie clip
- KME-200A External Earset-Microphone with flexible boom mic and tie clip
- **KME-H115** External Speaker-Microphone (light duty) KST-301 External Speaker-Microphone (heavy duty)
- CDI S-HTHX
 - Programming Kit (PC interface cable and software CD)



INTEK S.R.L. 16 Via G. Marconi. 20090 Segrate. Italy

Tel: +3902 26950451 - fax: +3902 26952185 - www.intek-radios.com - E-mail: info@intek-radios.com